

Battery Switches



701



701S



700

Contour Battery Master Switch

- Patented Contour Locking System allows switch to be a stand alone unit, or locked together with other switches
- Control knob can be removed by switching to counter-clockwise 45° position
- Three removable side plates for access of up to 1/0 cables plus a rear cover insulating the rear terminals against any short circuits. This ensures the switch meets ABYC requirements
- 2.1" (52 mm) hole for mounting

Battery Selector Switch

The 701S is the most compact selector switch available on the market. Housed in the same dimensions as the 701, and includes the same removable side plates and back cover ensuring that it meets ABYC requirements.

- While BEP recommends isolated battery systems as outlined with our distribution clusters, the 701S offers a simple economical way of separating two batteries

Please note selector switches will not separate electronics from harmful engine starting spikes.

Easyfit™ Battery Switch

Created primarily for installations where switches need to be recessed through varying thicknesses of panels.

- Easily removable threaded ring allows for panel thicknesses up to 3/4" (19 mm)
- Same features as the 701 with the removable knob 45° past the off position
- Includes removable back cover ensuring that it meets ABYC requirements
- Surface mount option offers a unique style compared to other switches available on the market
- Can easily be retro-fitted in place of most European post and lever type switches



720



721

Heavy-Duty Battery Switch

The 720 is well suited to larger vessels, being capable of handling the high electrical loads found on today's boats and RV's plus starting large diesel engines.

- Rated at 600A continuous and 2500A cranking
- Can be rear panel, or surface mounted
- Uses the same proven style of self cleaning sliding copper contact used inside the 701
- Can be locked with padlock for safely isolating circuits

Heavy-Duty Battery Selector Switch

The 721 is our heavy-duty selector switch. Housed in the same module as the 720, it includes the same removable plates and back cover.

Please note selector switches will not separate electronics from harmful engine starting spikes.

▶ POWER tip

BEP Battery Switch Construction

All BEP battery switches are molded in a high strength, fiber reinforced plastic which provides excellent high temperature performance, and the greatest resistance to chemicals that damage other plastic types.

Related Products



Interchangeable labeling system available
(Part # 713 or 715)
Label Sets page 80

Specifications - All recessed or surface mount, tin-plated copper studs & nuts, ignition-protected

Part #	OEM #	in LxWxH	mm LxWxH	Rating (A DC)			Voltage (V DC)	Operation	Stud size Studs x (in/mm)	Cable to meet rating (AWG/mm ²)
				Cont	Inter (5 min)	Crank (10 sec)				
700	700B	2.7" x 2.7" x 4.3"	68 x 68 x 110 mm	275	455	1250	48	On/Off	2x 3/8" / 10mm	3/0 / 95mm ²
701	701B	2.75" x 2.75" x 3"	69 x 69 x 75 mm	275	455	1250	48	On/Off	2x 3/8" / 10mm	3/0 / 95mm ²
701S	701S-B	2.75" x 2.75" x 3"	69 x 69 x 75 mm	200	300	1000	48	1-2-Both-Off	3x 5/16" / 8mm	1/0 / 50mm ²
720	720B	4" x 4" x 3.5"	102 x 102 x 90 mm	600	800	2500	48	On/Off	2x 1/2" / 12mm	2x 3/0 / 2x 95mm ²
721	721B	4" x 4" x 3.5"	102 x 102 x 90 mm	600	800	2500	48	1-2-Both-Off	2x 1/2" / 12mm	2x 2/0 / 2x 95mm ²